



## WELDING GENERATOR



TKG-180AC (Honda GX-390 Petrol Engine)



TKG-180AC (ATLANTA CF180F Diesel Engine)

### Technical Specifications :

MODEL	TKG-180AC	TKG-170DC	TKG-220DC
Welder Rated Current (A)	180 – 60%	170 – 50%	220A – 35%
Welder Rated Voltage (V)	22, 4 - 27, 2v	21, 8 - 26, 6v	21, 6 – 28, 8v
Welder Applicable Electrode $\Phi$	No. 10	No. 10	No. 10
AC Generator Rated Output (kw)	5	3	3.5
AC Generator Rated Frequency (Hz)	50	50	50
AC Generator Rated Voltage	230v – 21,7A	230v – 13A	230v – 15,2A
Engine Model	Honda GX-390 Gasoline Engine Recoil Start	Honda GX-390 Gasoline Engine Recoil Start	Honda GX-390 Gasoline Engine Recoil Start

*Designs and specifications are subject to change for improvement without prior notice.* 2007 - Rev. 5  
 LIGHT CONSTRUCTION MACHINERY - 69 WELDING GENERATOR (TKG-180AC, TKG-170DC & TKG-220DC)